

CFL Lamps										
Manufacturer	Model	Power	Compatibility	Number of CFL Lamps *	Dimming curve **	Dimming mode**	Low dimming limit ***	High dimming limit***	Observations	
E27	HEITRONIC	19519	25W	Yes	1	CFL 2	Trail	20%	100%	
	IKEA	SPARSAM	20W	Yes	1-12	CFL 2	Trail	18%	100%	
		TORNADO	15W	Yes	1-2	CFL 2	Lead	1%	100%	
	PHILIPS	PL-ELECTRONIC DIMMABLE	20W	Yes	1-4	CFL 2	Trail	1%	100%	
		SOFTONE	12W	Yes	1-3	CFL 2	Trail	8%	100%	
	GOVENA	DIMM	20W	Yes	1	CFL 1	Trail	1%	100%	For different dimming curve/mode of recommended ones flickering effects could appear at 100%.
	OSRAM	DULUX INTELLIGENT DIMMABLE	18W	Yes	1-3	CFL 2	Lead	12%	100%	
	MEGAMAN	MM42102	11W	Yes	1-3	CFL 2	Trail	14%	100%	Flickering during shutdown.
		MM46012	11W	Yes	1-3	CFL 1 or CFL 2	Trail	6%	100%	
WL218D		18W	Yes	1-9	CFL 2	Trail	11%	100%		
GU10	MEGAMAN	BR1411D	11W	Yes	1-3	CFL 2	Trail	5%	100%	

LED Lamps										
Manufacturer	Model	Power	Compatibility	Number of CFL Lamps *	Dimming curve **	Dimming mode**	Low dimming limit ***	High dimming limit***	Observations	
E27	OSRAM	PARATHOM CLASSIC A 60 ADVANCED	12W	Yes	1-10	LED 1 or LED 2	Trail	1%	100%	
		PARATHOM CL A 60	12W	Yes	1	LED 1 or LED 2	Lead/Trail	2%	100%	
	PHILIPS	MASTER LEDBULB MC DimTone	8W	Yes	1-8	LED 2	Trail	26%	100%	
		MASTER LEDbulb MV	17W	Yes	1-3	LED 1 or LED 2	Lead/Trail	1%	100%	
		LEDspot PAR 20	7W	Yes	1-2	LED 1 or LED 2	Lead/Trail	1%	100%	
		MASTER LEDbulb MV	12W	Yes	1	LED 1 or LED 2	Lead/Trail	1%	100%	
		MASTER LEDspot PAR 38 MV	18W	Yes	1-4	LED 1 or LED 2	Trail	1%	100%	
		MASTER LEDspot PAR 30s MV	12W	Yes	1-3	LED 1 or LED 2	Trail	2%	100%	
		LED GLOBE LG0708dv2	8W	Yes	1-3	LED 2	Lead/Trail	1%	100%	
	MEGAMAN	LED CLASSIC LG0408dv2	8W	Yes	1-3	LED 2	Lead/Trail	1%	100%	
		LG1907dv2	7W	Yes	1-10	Lineal, LED 1 or LED 2	Lead/Trail	1%	100%	
	VERBATIM	Classic A	9W	Yes	1	LED 1 or LED 2	Trail	1%	100%	
	LEDA	PAR38	18W	Yes	1-12	LED 2	Trail	10%	95%	It is not possible to dim more than 5 lamps per channel.
	CALEX		7W	Yes	1	LED 1 or LED 2	Trail	1%	100%	
GU10	OSRAM	PARATHOM PRO PAR16 35 ADVANCED	8W	Yes	1-3	LED 1 or LED 2	Lead/Trail	1%	100%	
		PARATHOM PRO PAR16 35 ADVANCED	9W	Yes	1-3	LED 1 or LED 2	Lead/Trail	1%	100%	
		PARATHOM PRO PAR16 50 36º	7,5W	Yes	1-8	LED 1 or LED 2	Trail	1%	100%	
	BGENOSTORE RENOVABLES	ONLINE MR 16	9W	Yes	1-5	Lineal, LED 1 or LED 2	Trail	1%	60%	
	PHILIPS	LEDspot GU10 MV DIMMABLE	5W	Yes	1-6	LED 1 or LED 2	Lead	1%	100%	
		MASTER LEDspot MV	7W	Yes	1	LED 1 or LED 2	Trail	1%	100%	
		MASTER LEDspot MV	4W	Yes	1	Lineal, LED 1 or LED 2	Trail	1%	100%	
		MASTER LEDspot MV	5,5W	Yes	1-4	LED 1 or LED 2	Lead/Trail	1%	100%	
		MASTER LEDspot MV D 4-35 28mA	4W	Yes	1-6	LED 1 or LED 2	Trail	1%	100%	
		MASTER LEDspot MV D 4-35 29mA	4W	Yes	1-14	LED 1 or LED 2	Lead/Trail	1%	100%	
	BRICOLUX		3W	Yes	1-3	Lineal, LED 1 or LED 2	Trail	1%	100%	
	CALEX		6W	Yes	1	LED 1 or LED 2	Lead/Trail	1%	100%	
	MEGAMAN	LR1108d-50H35D	8W	Yes	1-2	LED 1 or LED 2	Lead/Trail	1%	100%	
InteWatt	01-SLAGU10DNW	5W	Yes	1-2	LED 1 or LED 2	Lead/Trail	1%	100%		
CONECTOR LIBRE	FOKE	Barra LED (336 LEDs)	22W	Yes	1	Lineal, LED 1 or LED 2	Trail	1%	100%	

LED Lamps (12V)												
Manufacturer	Model	Transformer	Power	Compatibility	Number of CFL Lamps *	Dimming curve **	Dimming mode**	Low dimming limit ***	High dimming limit***	Observations		
VERBATIM	MR16	Niko 320-00004	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		Niko 320-00003	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		Niko 320-00002	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		MIMAVEN 150W	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		KRS LTD. 105	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		Layrton TRI-50 ENC-C PTC	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		MCT 5402.0340.439	6W	Yes	1	LED 1 or LED 2	Lead	1%	100%			
		ELT TCE 5/23-E	6W	Yes	1	LED 1 or LED 2	Trail	1%	100%			
		ELT TCE 7/23-E	6W	No						Blinks during the dimming.		
		OSRAM ET-ZE 60/220-240	6W	No						Does not turn on.		
		ThreeLine TT60	6W	No						Blinks during the dimming.		
		Niko 320-00101	6W	Yes	1	LED 1 or LED 2	Trail	20%	100%			
		OSRAM HALOTRONIC HTL 225/230-240	6W	No						Flash on the beginning of the dimming and there is not luminosity variation.		
		OSRAM HALOTRONIC HTL 150/230-240	6W	No						It is not possible to relative dimming.		
		OSRAM HALOTRONIC HTL 70/230-240	6W	No	1	LED 1 or LED 2	Lead	1%	100%			
		OSRAM HALOTRONIC HTL 105 230-240	6W	Yes	1	LED 2	Lead	1%	100%			
		PHILIPS Primaline 105 230-240	6W	No						It is not possible to relative dimming.		
		PHILIPS Primaline 70 230-240	6W	No						It is not possible to relative dimming.		
G5.3	PARATHOM MR16 20 36° ADVANCED	Niko 320-00004	5W	Yes	1-5	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.		
		Niko 320-00003	5W	Yes	1-5	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.		
		Niko 320-00002	5W	Yes	1-5	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.		
		MIMAVEN 150W	5W	Yes	1-5	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer and blink during the dimming.		
		KRS LTD. 105	5W	Yes	1-5	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.		
		Layrton TRI-50 ENC-C PTC	5W	Yes	1-5	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.		
		MCT 5402.0340.439	5W	No						It is not possible to dim correctly.		
		ELT TCE 5/23-E	5W	Yes	1-5	LED 1 or LED 2	Trail	1%	100%			
		ELT TCE 7/23-E	5W	Yes	1-5	LED 1 or LED 2	Trail	5%	100%			
		OSRAM ET-ZE 60/220-240	5W	No						After an operating time, stops dimming.		
		ThreeLine TT60	5W	No						It is not possible to dim correctly.		
		Niko 320-00101	5W	Yes	1-3	LED 1 or LED 2	Trail	30%	100%			
			5W	Yes	4-5	LED 1 or LED 2	Trail	3%	100%			
		OSRAM HALOTRONIC HTL 225/230-240	5W	Yes	1-4	LED 1 or LED 2	Trail	1%	100%	Dimming less than 5 lamps per channel, the luminosity is lower than normal operation.		
			5W	Yes	5	LED 1 or LED 2	Trail	1%	100%			
		OSRAM HALOTRONIC HTL 150/230-240	5W	Yes	1-5	LED 2	Trail	1%	100%	Blinks in the start of the dimming.		
		OSRAM HALOTRONIC HTL 70/230-240	5W	Yes	1-5	LED 2	Trail	1%	100%	Blinks in the start of the dimming.		
		OSRAM HALOTRONIC HTL 105 230-240	5W	Yes	1-5	LED 2	Trail	1%	100%	Blinks in the start of the dimming.		
		PHILIPS Primaline 105 230-240	5W	Yes	1-5	LED 2	Trail	2%	100%	Blinks in the start of the dimming.		
		PHILIPS Primaline 70 230-240	5W	Yes	3-5	LED 2	Trail	2%	100%	Blinks in the start of the dimming. There is no possibility of dimming less than 3 lamps per channel.		
		OSRAM	PARATHOM MR16 60 ADVANCED	Niko 320-00004	11W	No						It is not possible to dim correctly.
				Niko 320-00003	11W	No						It is not possible to dim correctly.
				Niko 320-00002	11W	No						It is not possible to dim correctly.
				MIMAVEN 150W	11W	No						It is not possible to dim correctly.
KRS LTD. 105	11W			No						It is not possible to dim correctly.		
Layrton TRI-50 ENC-C PTC	11W			No						It is not possible to dim correctly.		
MCT 5402.0340.439	11W			No						It is not possible to dim correctly.		
ELT TCE 5/23-E	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
ELT TCE 7/23-E	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
OSRAM ET-ZE 60/220-240	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
	11W			Yes	2	LED 1 or LED 2	Lead	1%	35%			
ThreeLine TT60	11W			Yes	3	LED 1 or LED 2	Lead	1%	100%			
Niko 320-00101	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
OSRAM HALOTRONIC HTL 225/230-240	11W			Yes	2	LED 2	Trail	57%	100%			
	11W			Yes	3	LED 2	Trail	16%	100%			
OSRAM HALOTRONIC HTL 150/230-240	11W			Yes	1-3	LED 1 or LED 2	Trail	2%	100%			
OSRAM HALOTRONIC HTL 70/230-240	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
OSRAM HALOTRONIC HTL 105 230-240	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
PHILIPS Primaline 105 230-240	11W			Yes	1-3	LED 1 or LED 2	Trail	1%	100%			
PHILIPS Primaline 70 230-240	11W			Yes	1-3	LED 2	Trail	1%	100%			

LED Lamps (12V)														
Manufacturer	Model	Transformer	Power	Compatibility	Number of CFL Lamps *	Dimming curve **	Dimming mode**	Low dimming limit ***	High dimming limit****	Observations				
G5.3	PHILIPS	MASTER LEDSPOT MR16 LV	Niko 320-00004	7W	Yes	1-2	Lineal	Lead	20%	100%	Blinks on the start of the dimming.			
			Niko 320-00003	7W	Yes	1	Lineal	Lead	45%	100%	Blinks on the start of the dimming.			
			Niko 320-00002	7W	Yes	2	Lineal	Lead	20%	100%	Blinks on the start of the dimming.			
			MIMAVEN 150W	7W	Yes	1-2	Lineal	Lead	25%	100%	Blinks on the start of the dimming.			
			KRS LTD. 105	7W	Yes	1-2	Lineal	Lead	25%	100%	Blinks on the start of the dimming.			
			Layrton TRI-50 ENC-C PTC	7W	Yes	1-2	Lineal	Lead	20%	100%	Blinks on the start of the dimming.			
			MCT 5402.0340.439	7W	Yes	1-2	Lineal	Lead	30%	100%	Blinks on the start of the dimming.			
			ELT TCE 5/23-E	7W	Yes	1	Lineal	Trail	23%	97%	Blinks on the start of the dimming.			
			ELT TCE 7/23-E	7W	Yes	2	Lineal	Trail	27%	100%	Blinks on the start of the dimming.			
			OSRAM ET-ZE 60/220-240	7W	Yes	1-2	Lineal	Trail	23%	100%	Blinks on the start of the dimming.			
			ThreeLine TT60	7W	Yes	2	Lineal	Lead	17%	100%	Blinks on the start of the dimming.			
			Niko 320-00101	7W	Yes	1	Lineal	Trail	25%	100%	Blinks on the start of the dimming.			
			OSRAM HALOTRONIC HTL 225/230-240	7W	Yes	2	Lineal	Trail	30%	100%	Blinks on the start of the dimming.			
			OSRAM HALOTRONIC HTL 150/230-240	7W	No						It is not possible to dim correctly.			
			OSRAM HALOTRONIC HTL 70/230-240	7W	Yes	1	Lineal	Lead	30%	100%	Blinks on the start of the dimming.			
			OSRAM HALOTRONIC HTL 105 230-240	7W	Yes	2	Lineal	Lead	35%	100%	Blinks on the start of the dimming.			
			OSRAM HALOTRONIC HTL 105 230-240	7W	Yes	1-2	Lineal	Lead	36%	100%	Blinks on the start of the dimming.			
			PHILIPS Primaline 105 230-240	7W	Yes	1	LED 2	Trail	25%	100%	Blinks on the start of the dimming.			
			PHILIPS Primaline 70 230-240	7W	Yes	2	LED 2	Trail	38%	100%	Blinks on the start of the dimming.			
			G53	VERBATIM	AR111	Niko 320-00004	16W	Yes	1	LED 1 or LED 2	Lead	1%	100%	
Niko 320-00003	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
Niko 320-00002	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
MIMAVEN 150W	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
KRS LTD. 105	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
Layrton TRI-50 ENC-C PTC	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
MCT 5402.0340.439	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
ELT TCE 5/23-E	16W	Yes				1	LED 1 or LED 2	Trail	1%	100%				
ELT TCE 7/23-E	16W	Yes				1	LED 1 or LED 2	Trail	1%	100%				
OSRAM ET-ZE 60/220-240	16W	Yes				1	LED 1 or LED 2	Trail	1%	100%				
ThreeLine TT60	16W	Yes				1	Lineal, LED 1 or LED 2	Lead	1%	100%				
Niko 320-00101	16W	Yes				1	LED 1 or LED 2	Lead	1%	100%				
OSRAM HALOTRONIC HTL 225/230-240	16W	Yes				1	LED 2	Trail	1%	100%				
OSRAM HALOTRONIC HTL 150/230-240	16W	Yes				1	Lineal, LED 1 or LED 2	Lead	1%	100%				
OSRAM HALOTRONIC HTL 70/230-240	16W	Yes				1	LED 2	Lead	1%	100%				
OSRAM HALOTRONIC HTL 105 230-240	16W	Yes				1	LED 2	Lead	1%	100%				
PHILIPS Primaline 105 230-240	16W	Yes				1	LED 2	Lead	6%	93%				
PHILIPS Primaline 70 230-240	16W	Yes				1	LED 2	Lead	2%	93%				
G53	SYLVANIA	REFLED AR111				Niko 320-00004	10W	Yes	1-4	LED 1 or LED 2	Lead	1%	100%	
						Niko 320-00003	10W	Yes	1-4	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.
			Niko 320-00002	10W	Yes	1-4	LED 2	Lead	1%	100%				
			MIMAVEN 150W	10W	Yes	1-4	LED 1 or LED 2	Lead	1%	100%				
			KRS LTD. 105	10W	Yes	1-4	LED 1 or LED 2	Lead	1%	100%				
			Layrton TRI-50 ENC-C PTC	10W	Yes	1-4	LED 1 or LED 2	Lead	1%	100%				
			MCT 5402.0340.439	10W	Yes	1-4	LED 1 or LED 2	Lead	2%	100%				
			ELT TCE 5/23-E	10W	Yes	1-4	LED 1 or LED 2	Trail	1%	100%				
			ELT TCE 7/23-E	10W	Yes	1-4	LED 1 or LED 2	Trail	1%	100%				
			OSRAM ET-ZE 60/220-240	10W	Yes	1-4	LED 2	Trail	1%	100%				
			ThreeLine TT60	10W	Yes	2-4	LED 1 or LED 2	Lead	1%	100%				
			Niko 320-00101	10W	Yes	1-4	LED 2	Lead/Trail	1%	100%				
			OSRAM HALOTRONIC HTL 225/230-240	10W	Yes	3	Lineal	Trail	15%	100%				
			OSRAM HALOTRONIC HTL 225/230-240	10W	Yes	4	Lineal	Trail	13%	100%				
			OSRAM HALOTRONIC HTL 150/230-240	10W	Yes	2	LED 2	Trail	5%	100%				
			OSRAM HALOTRONIC HTL 150/230-240	10W	Yes	3-4	LED 2	Trail	1%	100%				
			OSRAM HALOTRONIC HTL 70/230-240	10W	Yes	1-4	LED 1 or LED 2	Trail	1%	100%				
			OSRAM HALOTRONIC HTL 105 230-240	10W	Yes	1-4	LED 2	Trail	1%	100%				
			PHILIPS Primaline 105 230-240	10W	Yes	1	LED 2	Trail	15%	100%				
			PHILIPS Primaline 70 230-240	10W	Yes	2-4	LED 2	Trail	1%	100%				
PHILIPS Primaline 70 230-240	10W	Yes	1	LED 2	Trail	18%	100%							
PHILIPS Primaline 70 230-240	10W	Yes	2-4	LED 2	Trail	1%	100%							

LED Lamps (12V)											
Manufacturer	Model	Transformer	Power	Compatibility	Number of CFL Lamps *	Dimming curve **	Dimming mode **	Low dimming limit ***	High dimming limit****	Observations	
G.53	OSRAM	PARATHOM PRO LEDSPOT111 50 24 ⁹ ADVANCED	Niko 320-00004	12W	Yes	1-3	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.
			Niko 320-00003	12W	Yes	1-3	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.
			Niko 320-00002	12W	Yes	1-3	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.
			MIMAVEN 150W	12W	Yes	1-3	LED 1 or LED 2	Lead	1%	100%	
			KRS LTD. 105	12W	Yes	1-3	LED 1 or LED 2	Lead	1%	100%	Noise in the transformer.
			Layrton TRI-50 ENC-C PTC	12W	Yes	1-3	LED 2	Lead	1%	100%	Noise in the transformer.
			MCT 5402.0340.439	12W	Yes	1-3	LED 2	Lead	1%	100%	Noise in the transformer.
			ELT TCE 5/23-E	12W	Yes	1-3	LED 1 or LED 2	Trail	1%	100%	
			ELT TCE 7/23-E	12W	Yes	2-3	LED 2	Trail	1%	100%	It is not possible to dim less than 2 lamps per channel.
			OSRAM ET-ZE 60/220-240	12W	Yes	1-3	LED 2	Trail	1%	100%	
			ThreeLine TT60	12W	Yes	1	LED 2	Trail	16%	89%	
				12W	Yes	2-3	LED 2	Trail	1%	100%	
			Niko 320-00101	12W	Yes	1-3	LED 1 or LED 2	Trail	1%	100%	
			OSRAM HALOTRONIC HTL 225/230-240	12W	Yes	2	LED 2	Trail	1%	100%	
				12W	Yes	3	LED 2	Trail	10%	100%	
			OSRAM HALOTRONIC HTL 150/230-240	12W	Yes	1-3	LED 1 or LED 2	Trail	2%	100%	
			OSRAM HALOTRONIC HTL 70/230-240	12W	Yes	1-3	LED 1 or LED 2	Trail	1%	100%	
			OSRAM HALOTRONIC HTL 105 230-240	12W	Yes	1-3	LED 1 or LED 2	Trail	1%	100%	
			PHILIPS Primaline 105 230-240	12W	Yes	2-3	LED 1 or LED 2	Trail	1%	100%	It is not possible to dim less than 2 lamps per channel.
				12W	Yes	1	LED 1 or LED 2	Trail	2%	100%	
	12W	Yes	2-3	LED 1 or LED 2	Trail	1%	100%				
G.53	PHILIPS	MASTER LEDSPOT AR111 LV	Niko 320-00004	15W	Yes	1	Lineal	Lead	2%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	2-3	Lineal	Lead	25%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	1	Lineal	Lead	1%	100%	There is a little oscilation in the beginning of the dimming.
			Niko 320-00003	15W	Yes	2-3	Lineal	Lead	30%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	1	Lineal	Lead	20%	100%	There is a little oscilation in the beginning of the dimming.
			Niko 320-00002	15W	Yes	2-3	Lineal	Lead	35%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	1	Lineal	Lead	25%	100%	
			MIMAVEN 150W	15W	Yes	2-3	Lineal	Lead	20%	100%	
				15W	Yes	1-2	Lineal	Lead	20%	85%	Noise in the transformer.
			KRS LTD. 105	15W	Yes	3	Lineal	Lead	25%	85%	Noise in the transformer.
			Layrton TRI-50 ENC-C PTC	15W	Yes	1-2	Lineal	Lead	25%	100%	
				15W	Yes	3	Lineal	Lead	31%	100%	
			MCT 5402.0340.439	15W	Yes	1-3	Lineal	Lead	20%	100%	Noise in the transformer.
			ELT TCE 5/23-E	15W	Yes	1	Lineal	Trail	20%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	2-3	Lineal	Trail	30%	100%	There is a little oscilation in the beginning of the dimming.
			ELT TCE 7/23-E	15W	Yes	1	Lineal	Trail	25%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	2-3	Lineal	Trail	35%	100%	There is a little oscilation in the beginning of the dimming.
			OSRAM ET-ZE 60/220-240	15W	Yes	1	Lineal	Trail	30%	100%	There is a little oscilation in the beginning of the dimming.
				15W	Yes	2-3	Lineal	Trail	35%	100%	There is a little oscilation in the beginning of the dimming.
			ThreeLine TT60	15W	Yes	1-3	Lineal	Lead	30%	100%	There is a little oscilation in the beginning of the dimming.
Niko 320-00101	15W	Yes	1-2	Lineal	Lead	30%	100%	There is a little oscilation in the beginning of the dimming.			
	15W	Yes	3	Lineal	Lead	45%	100%	There is a little oscilation in the beginning of the dimming.			
OSRAM HALOTRONIC HTL 225/230-240	15W	No						It is not possible to dim correctly.			
OSRAM HALOTRONIC HTL 150/230-240	15W	No						It is not possible to dim correctly.			
OSRAM HALOTRONIC HTL 70/230-240	15W	Yes	1-3	Lineal	Trail	30%	100%	There is a little oscilation in the beginning of the dimming.			
OSRAM HALOTRONIC HTL 105 230-240	15W	Yes	1-2	Lineal	Lead	35%	100%	There is a little oscilation in the beginning of the dimming.			
	15W	Yes	3	Lineal	Lead	25%	100%	There is a little oscilation in the beginning of the dimming.			
PHILIPS Primaline 105 230-240	15W	No						It is not possible to dim correctly.			
PHILIPS Primaline 70 230-240	15W	Yes	3	Lineal	Lead	35%	90%	There is a little oscilation in the beginning of the dimming. It isn't possible to dim less than 3 lamps per channel.			

* This information is based in the test with DIMinBOX DX2 1.0 and a specific number of lamps of each type. It could control a higher number of lamps but it is ALWAYS necessary to test that number of lamps.

** The dimming curve and mode to configure in ETS parameters is based in the tests with the indicated number of lamps. It is necessary to test the number of lamps that will be installed with DIMinBOX DX2.

*** Some lamps flicker in low dimming levels or are only dimmable from a specific level, so it is necessary to set a Low Dimming Limit. And also, some lamps flicker in high dimming levels, because of that, it is necessary to set a High Dimming Limit.